



A leading worldwide distributor since 1982

Hysecurity Nice Apollo 1050 Board with OXI CH1 Invalid Receiver Issue

An unknown number of operators with 1050 boards do not have the channel programmed for the plug-in OXI receiver.



- Did the remote program to the receiver? (indicated by three blinks on the receiver)
- If no, re-pair the remote.
- If yes, press “Function”
- Press down arrow to #4 “Radio”
- Press “OK”
- If it says “Invalid”, follow the next steps
 - o Press “OK”, “Invalid” should be flashing
 - o Press up arrow until “Step” is displayed
 - o Press “OK”
 - o Press “Display”
 - o Press “OK”
 - o Try Remote
- If “Step” is displayed, or if the above steps did not correct the problem, please contact Nice Technical Support at 800-321-9947.
- To set all radio channels back to default:

Push function > 10: Default > Default System (N) > Default Radio Ch (Y) > Events (N) > Charger (N)

DF Supply, Inc. • 8500 Hadden Road • Twinsburg, OH 44087

Toll-free: (800) 878-7829 • Local: (330) 650-9226 • Fax: (330) 650-9004

Email: sales@dfsupplyinc.com • Web: www.dfsupplyinc.com