



*A leading worldwide distributor since 1982*

## **Nice Apollo 928 Keypad With 636/936/1050 Board Wiring Installation**

In order to hookup your new Nice Apollo 928 Keypad to either a 636, 936, or 1050 Board operated opener, you'll need to follow the below color coordinating chart. This chart will show which wire corresponds to the proper input connection on your gate operator.

<b>Keypad Wire Color</b>	<b>636 Board Connector #</b>	<b>936 Board Connector #</b>	<b>1050 Board Connector #</b>
Red	12V	+12V-a	Pin 11 (V+)
Black	GND	GRD	Pin 10 (GND)
Brown	GND	GRD	Pin 41 (GND)
Orange	FREE EXIT	EXIT	Pin 39 (OPEN)

DF Supply, Inc. • 10050 Wellman Road • Streetsboro, OH 44241

Toll-free: (800) 878-7829 • Local: (330) 650-9226 • Fax: (330) 650-9004

Email: [sales@dfsupplyinc.com](mailto:sales@dfsupplyinc.com) • Web: [www.dfsupplyinc.com](http://www.dfsupplyinc.com)